

DATA SHEET : CKRF6163XS03

Broadband SPDT Switch for Dual-Band Wireless LAN



Features


- Control voltage :
 $VC(H) = 1.8 \text{ to } 5.0 \text{ V (3.0V TYP.)}$
 $VC(L) = -0.2 \text{ to } 0.2 \text{ V (0V TYP.)}$
- Low insertion loss :
 $L_{ins1} = 0.40 \text{ dB TYP. @ } f = 2.4 \text{ to } 2.5 \text{ GHz}$
 $L_{ins2} = 0.50 \text{ dB TYP. @ } f = 4.9 \text{ to } 6.0 \text{ GHz}$
- High isolation :
 $ISL1 = 40 \text{ dB TYP. @ } f = 2.4 \text{ to } 2.5 \text{ GHz}$
 $ISL2 = 31 \text{ dB TYP. @ } f = 4.9 \text{ to } 6.0 \text{ GHz}$
- Handling power :
 $P_{in(1dB)} = +33 \text{ dBm TYP. @ } f = 2.5 \text{ GHz,}$
 $VC(H) = 3.0 \text{ V, } VC(L) = 0 \text{ V}$
 $P_{in(1dB)} = +32 \text{ dBm TYP. @ } f = 6.0 \text{ GHz,}$
 $VC(H) = 3.0 \text{ V, } VC(L) = 0 \text{ V}$

Package

- 6-pin XSON Package
(1.5mm x 1.5mm x 0.37mm)

Description


- The CKRF6163XS03 is a GaAs MMIC SPDT(Single Pole Double Throw) switch which was developed for 2.4 GHz and 6 GHz dual-band wireless LAN.



Applications

- Dual-band wireless LAN
(IEEE802.11a/b/g/n), etc.

Pin Configuration and Internal Block Diagram



Pin No.	Pin Name
1	GND
2	VC2
3	RF2
4	RF1
5	VC1
6	RFC

Remark Exposed pad : GND

Ordering Information

Part Number	Order Number	Package	Marking	Supplying Form
CKRF6163XS03-C2	CKRF6163XS03-C2	6-pin plastic TSO8 (Pb-Free)	106	• Embossed tape 8 mm wide • Pin 1, 6 face the perforation side of the tape • Qty 10 kpcs/reel

DATA SHEET : CKRF6163XS03



Broadband SPDT Switch for Dual-Band Wireless LAN

Absolute Maximum Ratings

(T_A = +25°C, unless otherwise specified)

Parameter	Symbol	Rating	Unit
Control Voltage	VC	6.0 ^{Note 1}	V
Input Power	P _{in}	+33.5 ^{Note 2}	dBm
Operating Ambient Temperature	T _A	-45~+85	°C
Storage Temperature	T _{stg}	-55~+150	°C

- Note**
1. $|VC1 - VC2| \leq 6.0V$
 2. $3.0V \leq |VC1 - VC2| \leq 5.0V$

Recommended Operating Range

(T_A = +25°C, unless otherwise specified)

Parameter	Symbol	MIN.	TYP.	MAX.	Unit
Operating Frequency	f1	2.4	-	2.5	GHz
	f2	4.9	-	6.0	GHz
Switch Control Voltage (H)	VC(H)	+1.8	+3.0	+5.0	V
Switch Control Voltage (L)	VC(L)	-0.2	0	+0.2	V

Truth Table

VC1	VC2	RFC-RF1	RFC-RF2
High	Low	OFF	ON
Low	High	ON	OFF

DATA SHEET : CKRF6163XS03



Broadband SPDT Switch for Dual-Band Wireless LAN

Electrical Characteristics

($T_A=+25\text{ }^\circ\text{C}$, $V_C(H)=3.0\text{V}$, $V_C(L)=0\text{V}$, $Z_o=50\ \Omega$, DC Block Capacitance=4pF, unless otherwise specified)

Parameter	Symbol	Test Conditions	MIN.	TYP.	MAX.	Unit
Insertion Loss	Lins1	f = 2.4 to 2.5 GHz	-	0.40	0.60	dB
	Lins2	f = 4.9 to 6.0 GHz	-	0.50	0.80	dB
Isolation	ISL1	f = 2.4 to 2.5 GHz	37	40	-	dB
	ISL2	f = 4.9 to 6.0 GHz	28	31	-	dB
Input Return Loss	RLin1	f = 2.4 to 2.5 GHz	-	15	-	dB
	RLin2	f = 4.9 to 6.0 GHz	-	15	-	dB
Output Return Loss	RLout1	f = 2.4 to 2.5 GHz	-	15	-	dB
	RLout2	f = 4.9 to 6.0 GHz	-	15	-	dB
1 dB Loss Compression Input Power Note	$P_{in(1dB)}$	f = 2.4 to 2.5 GHz, VC(H)=1.8V, VC(L)=0V	-	+29	-	dBm
		f = 2.4 to 2.5 GHz, VC(H)=3.0V, VC(L)=0V	-	+33	-	dBm
		f = 4.9 to 6.0 GHz, VC(H)=1.8V, VC(L)=0V	-	+26	-	dBm
		f = 4.9 to 6.0 GHz VC(H)=3.0V, VC(L)=0V	-	+32	-	dBm
3rd Order Input Intercept Point	IIP ₃	f = 2.5GHz 2-tone 5MHz Spacing	-	+55	-	dBm
Switch Control Speed	t _{sw}	50% CTL to 90/10%	-	80	-	ns
Switch Control Current	I _{cont}	RF None	-	2	-	μA


Note $P_{in(1dB)}$ is the measured input power level when the insertion loss increases 1dB more than that of the linear range.

DATA SHEET : CKRF6163XS03



Broadband SPDT Switch for Dual-Band Wireless LAN


Evaluation Circuit



The application circuits and their parameters are for reference only and are not intended for use in actual design-ins. This device is used it is necessary to use DC Block Capacitance.

Package Dimensions

6-pin Plastic XSON (Unit : mm)



[CAUTION]

- All information included in this document is current as of the date this document is issued. Such information, however, is subject to change without any prior notice.
- You should not alter, modify, copy, or otherwise misappropriate any CDK product, whether in whole or in part.
- CDK does not assume any liability for infringement of patents, copyrights, or other intellectual property rights of third parties by or arising from the use of CDK products or technical information described in this document. No license, express, implied or otherwise, is granted hereby under any patents, copyrights or other intellectual property rights of CDK or others.
- Descriptions of circuits, software and other related information in this document are provided only to illustrate the operation of semiconductor products and application examples. You are fully responsible for the incorporation of these circuits, software, and information in the design of your equipment. CDK assumes no responsibility for any losses incurred by you or third parties arising from the use of these circuits, software, or information.
- CDK has used reasonable care in preparing the information included in this document, but CDK does not warrant that such information is error free. CDK assumes no liability whatsoever for any damages incurred by you resulting from errors in or omissions from the information included herein.
- Although CDK endeavors to improve the quality and reliability of its products, semiconductor products have specific characteristics such as the occurrence of failure at a certain rate and malfunctions under certain use conditions. Please be sure to implement safety measures to guard them against the possibility of physical injury, and injury or damage caused by fire in the event of the failure of a CDK product, such as safety design for hardware and software including but not limited to redundancy, fire control and malfunction prevention, appropriate treatment for aging degradation or any other appropriate measures
Because the evaluation of microcomputer software alone is very difficult, please evaluate the safety of the final products or system manufactured by you.
- Please use CDK products in compliance with all applicable laws and regulations that regulate the inclusion or use of controlled substances, including without limitation, the EU RoHS Directive.
CDK assumes no liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations.
- This document may not be reproduced or duplicated, in any form, in whole or in part, without prior written consent of CDK.
- Please contact a CDK if you have any questions regarding the information contained in this document or CDK products, or if you have any other inquiries.

[Caution in the gallium arsenide (GaAs) product handling]

This product uses gallium arsenide (GaAs) of the toxic substance appointed in laws and ordinances. GaAs vapor and powder are hazardous to human health if inhaled or ingested.

- Do not dispose in fire or break up this product.
- Do not chemically make gas or powder with this product.
- When discard this product, please obey the law of your country.
- Do not lick the product or in any way allow it to enter the mouth.

[CAUTION]

Although this device is designed to be as robust as possible, ESD (Electrostatic Discharge) can damage this device. This device must be protected at all times from ESD. Static charges may easily produce potentials of several kilovolts on the human body or equipment, which can discharge without detection. Industry-standard ESD precautions should be used at all times.

CHUO DENSHI KOGYO CO., LTD
3400 Kooyama, Matsubase, Uki-City,
Kumamoto 869-0512, Japan
Tel : +81-964-32-2730
Fax : +81-964-32-3549
URL : <http://www.en.cdk.co.jp/>

Contact info for inquiries
Electronic Devices Division Sales and Planning Department
TEL : +81-964-32-2750
E-mail : info@cdk.co.jp
FAX : +81-964-32-3549
